

AMLc

Multi-channel current



DESCRIPTION

Use of probes with current output, for all types of instrumentation.

Makes already installed probes connected or facilitates installation for new installations; generally does not require external power supply.

Compatible with water quality sensor, load cell, pressure cells, extensometer, piezometer, ...

Each sensor is autonomous; it doesn't need another box nor a sending station

APPLICATIONS

All types of instrumentation.

SENSOR CHARACTERISTICS

DATA RECORDING

Local measurement interval	1 second (via Bluetooth application)
Data reporting interval	1 hour (configurable)
Reported data	Current of the connected probes Case temperature Battery voltage

CURRENT PROBE

Measurement principle	Current
Measuring range	4 ... 20mA
Resolution	<0,5 μ A

TEMPERATURE SENSOR INSIDE THE HOUSING

Measuring principle	NTC
Measuring range	-55 ... +125°C
Resolution	0,6°C (-5 ... +50°C)

LONG DISTANCE RADIO

Radio technology	LoRaWAN
Security	AES-128 data encryption
Supported features	LoRa private or operated, OTAA
Radio range	Up to 15 km
Transmitted power	Up to 20 dBm (adaptive)
Receiver sensitivity	-142 dBm
Frequency band	868 MHz (EU), 915MHz (US, AS, AU)
Antenna	Internal or external to the housing

LOCAL RADIO

Radio technology	Bluetooth Low Energy
Radio range	Up to 40m
Transmitted power	Up to 4 dBm
Receiver sensitivity	-96 dBm
Frequency band	2.4 GHz ISM
Antenna	Internal to the box

POWER SUPPLY

Battery type	Lithium-Ion	
Power consumption	< 1mW	
Battery life *	Measurement period	Duration (up to)
	1 hour	5 years

* Indicative duration, for use in the conditions of use and according to the number of connected sensors, their characteristics and their validation by our engineering department

SENSOR

Operating temperature	-30 ... +85°C
Dimension	135 x 135 x 60 mm
Weight	350g
Internal memory	1024 measurements
Case	Polycarbonate (weather, UV and impact resistant) Decompressor against condensation IP65, IK07 Fixing brackets

ORDER REFERENCES

ORDER REFERENCES

AMLc-01	Current sensor with 1 input
AMLc-02	Current sensor with 2 inputs
AMLc-03	Current sensor with 3 inputs
AMLc-04	Current sensor with 4 inputs
AMLc-05	Current sensor with 5 inputs
AMLc-06	Current sensor with 6 inputs
AMLc-07	Current sensor with 7 inputs
AMLc-08	Current sensor with 8 inputs

Other options : contact us

WARNINGS

Specifications and information in this document are subject to change without notice.

A3IP products are not warranted or licensed for use as a critical component for medical or other life-saving or life-sustaining applications, or other applications where failure could reasonably be expected to cause serious injury, death, or damage to any structure, work or building.

In addition, devices are indications and decision aids and cannot be used in alarm or critical applications.

CONTACT

<https://www.a3ip.com>

contact@a3ip.com

+33 (0)2 40 94 78 41

A3IP
Bâtiment Placel
Route de Vannes
44880 SAUTRON
France